

A. INDEX

1. Department Price Changes
2. Department Name Changes
3. PLU Price Changes
4. PLU Name Changes
5. Programming Time and Date
6. Alpha Code Characters
7. Reports

1. Price Change

1. *TURN* Turn key to the PROGRAM position
2. *DISPLAY* Should show P1
3. *ENTER* New price (without using decimal point)
4. *PRESS* Preset item button that you wish to change
5. *REPEAT* Steps 3 to 4 until finished
6. *PRESS* Subtotal button to finish
7. *TURN* Key back to REG1

2. Name Change

1. *TURN* Turn key to the PROGRAM position
2. *ENTER* 2
3. *PRESS* Subtotal button
4. *DISPLAY* Should show P2
5. *TYPE* New department description using
2 digit codes as listed below (putting
a decimal point between each code)
6. *PRESS* 00 button
7. *PRESS* Department key to be changed
8. *REPEAT* Steps 5 to 7 until finished
9. *PRESS* Subtotal button to finish
10. *TURN* Key back to REG1

Example: To program MISC
Turn key to PGM
Enter 2 then subtotal
Enter 77 . 73 . 83 . 67 .
Press 00 key
Press MISC key
Turn key back to REG

3. PLU Price Change

1. *TURN* Turn key to the PROGRAM position
2. *DISPLAY* Should show P1
3. *ENTER* PLU number
4. *PRESS* PLU key on keyboard
5. *ENTER* New price (without using decimal point)
6. *PRESS* CASH key
7. *REPEAT* Steps 3 to 6 until finished
8. *PRESS* Subtotal button to finish
9. *TURN* Key back to REG1

To get PLU report to check numbers used

Turn key to Program
Enter 6
Press subtotal
Enter 206
Press subtotal key

4. PLU Name Change

1. *TURN* Turn key to the PROGRAM position
2. *ENTER* 2
3. *PRESS* Subtotal button
4. *DISPLAY* Should show P2
5. *ENTER* PLU number (enter 00 key before PLU#)
5. *TYPE* New department description using 2 digit codes (putting a decimal point between each code)
6. *PRESS* 00 button
7. *PRESS* CASH key
8. *REPEAT* Steps 5 to 7 until finished
9. *PRESS* Subtotal button to finish
10. *TURN* Key back to REG1

To get PLU report to check numbers used

Turn key to Program
Enter 6
Press subtotal
Enter 206
Press subtotal key

5. Date and Time Programming

1. *TURN* Turn key to the PROGRAM position
2. *DISPLAY* Should show P1
3. *ENTER* Date in the following format:-
(for days 1 to 9, be sure to enter them as 01 to 09. Enter months 1 to 9 as 01 to 09)

YYMMDD

YY = Year
MM = Month
DD = Day
4. *PRESS* X / Date Time button
5. *ENTER* Time in the following format:-

(for hours 1 to 9, be sure to enter them as 01to 09. Enter minutes 1 to 9 as 01 to 09)

HHMM

HH = Hour
MM = Minute
6. *PRESS* X / Time Date button
7. *TURN* Key back to REG1

6. Alpha Character Codes

| | | | |
|----|---|----|---|
| 65 | A | 78 | N |
| 66 | B | 79 | O |
| 67 | C | 80 | P |
| 68 | D | 81 | Q |
| 69 | E | 82 | R |
| 70 | F | 83 | S |
| 71 | G | 84 | T |
| 72 | H | 85 | U |
| 73 | I | 86 | V |
| 74 | J | 87 | W |
| 75 | K | 88 | X |
| 76 | L | 89 | Y |
| 77 | M | 90 | Z |

| | | | |
|----|----|----|---|
| 36 | \$ | 52 | 4 |
| 38 | & | 53 | 5 |
| 48 | 0 | 54 | 6 |
| 49 | 1 | 55 | 7 |
| 50 | 2 | 56 | 8 |
| 51 | 3 | 57 | 9 |

7. Reports

Daily READ

1. *TURN* Key to the X position
2. *PRESS* Cash key

Daily READ & RESET

1. *TURN* Key to the Z position
2. *PRESS* Cash key

Weekly READ & RESET

1. *Turn* Key to the Z position
2. *Press* 200 Cash

Monthly READ & RESET

1. *Turn* Key to the Z position
2. *Press* 400 Cash